

A GENERATOR SET HAVING AN INVERTER

BACKGROUND OF THE INVENTION

Field of the Invention

5 The present invention relates to a generator set having an inverter and particularly to a generator set having an inverter where a generator of particularly a magnetic type can be operated at high efficiency within a wider range of the revolution.

10 Description of the Related Art

 It has increasingly been common that an engine operated generator for use as an alternating current power source is equipped with an inverter for stabilizing the output frequency. For example, such a generator set having an
15 inverter is disclosed in Japanese Patent Laid-open Publication (Heisei) 11-308896 where an alternating current power is generated by an engine operated generator, converted into a direct current form, and converted again by the inverter into an alternating current form of a commercial frequency.
20 Because its frequency does not depend on the revolution of the engine, the output of the generator set having an inverter can be adjusted to a desired power output which is preset or determined to match the magnitude of load by controlling the revolution of the engine.

25 Fig. 9 illustrates a power output characteristic of a generator of a magnetic type where the revolution is a

5
Lab.
C2
pm-t.

10

20

level V. On the other hand, if the revolution is too high, the power output will be declined due to preferable utilization of the over-current side of the characteristic.

SUMMARY OF THE INVENTION

5 It is hence an object of the present invention to provide a generator set having an inverter which can be operated in a wider range of the revolution while eliminating the foregoing drawbacks.

10 As a first feature of the present invention, a generator set having a converter composed of semiconductor rectifying devices for rectifying the power output of a magnetic generator and an inverter for converting a direct current output of the converter into an alternating current form of a particular frequency is provided comprising: a
15 semiconductor rectifying device driving means for controlling the conduction of the semiconductor rectifying devices to maintain the voltage output of the converter at a target voltage level; a revolution detecting means for detecting the number of revolutions of the magnetic
20 generator; and a target voltage setting means for determining the target voltage level so that the target voltage level show a positive characteristic to the revolution detected.

25 This allows the target voltage level to be set to a lower value at a lower range of the revolution of the magnetic generator and a higher value at a higher range of the same. Accordingly, as the magnetic generator is increased in the

5
10
15
20
25
voltage output substantially in proportion to the revolution,
it can produce a voltage output of the target level at the
lower range of the revolution. Also, its voltage output can
be close to the maximum level without lowering the efficiency
when the generator is operated at the higher range of the
revolution. As a result, the useful range of the revolution
of the generator can be increased.

As a second feature of the present invention, a generator
set having an inverter may further comprise an engine
revolution controlling means for controlling the revolution
of an engine to drive the generator so that the conduction
rate of the semiconductor rectifying devices is converged
on a predetermined target rate, wherein the controlling of
the revolution of the engine is implemented by adjusting
the supply of fuel to the engine.

This allows the revolution of the engine to be modified
within a wider range thus controlling the conduction rate
of the semiconductor rectifying devices to a desired level.

As a third feature of the present invention, the engine
revolution controlling means may be arranged to decrease
the revolutions of the engine when the deviation of the
conduction rate from the target rate is positive and increase
the same when negative. As a fourth feature of the present
invention, a rate of change of revolution of the engine is
greater at an increase than at a decrease thereof.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a functional block diagram of a generator set having an inverter showing one embodiment of the present invention;

Fig. 2 is a diagram showing the relationship between the target voltage and the revolution of an engine;

Fig. 3 is a functional block diagram showing a primary part of a thyristor drive unit;

Fig. 4 is a diagram showing the relationship between the target voltage level and the power output of a magnetic generator in the embodiment;

Fig. 5 is a functional block diagram of a primary part of the generator set having an inverter with an output voltage controller of the inverter;

Fig. 6 is a functional block diagram of a primary part of a fuel flow controller;

Fig. 7 is an explanatory view showing the angle of conduction of the thyristors (the rate of conduction of semiconductor devices);

Fig. 8 illustrates the relationship between the deviation of the conduction angle and the adjustment of the target revolution; and

Fig. 9 illustrates the relationship between the target voltage level and the output of a conventional generator.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

An embodiment of the present invention will be described in more detail referring to the relevant drawings. Fig. 1

5

10

15

20

25

is a block diagram showing an arrangement of the generator set having an inverter of the embodiment. A magnetic type multi-pole generator 1 (referred to as simply a generator hereinafter) is driven by an (internal combustion) engine 2 to generate a multi-phase (commonly three-phase) alternating current power output. The alternating current power output is full-wave rectified to a direct current form by a converter 3 which comprises a rectifier circuit having thyristors (as semiconductor rectifier devices) connected in a bridge form. The direct current power output is then transferred to an inverter 4 which is connected at its output to and provides an external load 5 with a single-phase power output of a commercial frequency (e.g. 50 Hz). A stepping motor 7 is also provided for controlling the opening of a throttle valve 6 of the engine 2. More specifically, as the opening of the throttle valve 6 is controlled by the number of pulses, it determines the revolution of the engine 2. The engine 2 may be of a fuel injection type of which the revolutions is controlled by the duration of fuel injection.

A voltage detector 8 detects an output voltage of the converter 3. A thyristor drive unit 9 compares the output voltage of the converter 3 with a target voltage level (will be described later in more detail) and determines the conduction of thyristors in the converter 3 using a known manner so that the actual output voltage of the converter 3 detected by the voltage detector 8 is equal to the target

voltage level. This allows the output of the converter 3 to stay at the target voltage level within the controlling range of conduction angle of the thyristors.

5
pub.
AS

10

The target voltage level is predetermined as a function of the revolution of the engine by the following manner. Fig. 2 is a diagram showing the relationship between the target voltage level and the revolution of the engine. As shown, the target voltage level is set to V_0 when the revolution N_e of the engine is lower than 3000 rpm and V_1 , which is greater than V_0 , when higher than 5000 rpm. The target voltage level is gradually varied when the revolution N_e ranges from 3000 to 5000 rpm. For example, the target voltage level may be calculated from Equation 1,

$$VDC = 145 + (N_e / 256) \dots (1)$$

15

According to the equation 1, when the revolution N_e of the engine is 3000, 4300, or 5000 rpm, the target voltage level is 156.7V, 161.8V, or 164.5V respectively. The calculation of the target voltage level is not limited to the above equation but may be implemented by any appropriate manner

20

where an optimum of the power output can be obtained at a given revolution with relation to the characteristics of the generator.

25

Fig. 3 is a functional block diagram showing a primary part of the thyristor drive unit 9 assigned with the target voltage level. As shown, a revolution detector 106 measures the revolution N_e . The revolution N_e is then transferred

5
P. 115

to a target voltage calculator 91 where it is used for calculating the target voltage level VDC from Equation 1. A voltage deviation detector 92 compares the direct current voltage from the voltage detector 8 or the voltage output of the converter 3 with the target voltage level VDC to determine a deviation from the target voltage level. The deviation is transferred to a thyristor drive circuit 93 for controlling the conduction of the thyristors as explained with Fig. 1.

10 Because the target voltage level VDC is varied corresponding to the revolution of the engine, the following advantage can be achieved. Fig. 4 illustrates the relationship between the target voltage level VDC and the output of the generator 1, where like items are denoted by
15 like numerals as those shown in Fig. 9. The direct current voltage at the input of the inverter is controlled to be equal to the target voltage level VDC. As apparent, while the direct current voltage level at the input of the inverter is maintained equal to the target voltage level VDC, three
20 different outputs of the generator at L, M, and H of the revolution are expressed by the points p, q(=q'), and r on the curves Ap, Bp, and Cp respectively. As compared with the prior art where the target voltage level is set to a fixed value V, the output at a lower revolution L is increased
25 from r' to r denoted by the arrow and at a higher revolution H from p' to p. Also, the output at a medium revolution M

Pub.
1A5
cond.
5

is substantially at its maximum. More specifically, a high level of the output can be obtained throughout a wider range of revolution. In an experimental example, the range of revolution to be used actually was increased by generally 200 rpm.

As the target voltage level VDC is varied, the input voltage of the inverter 4 may change. This change can be offset more or less by the inverter 4 equipped with a voltage controlling function such as PMW. The PMW technique allows the input voltage of the inverter 4 to stay higher than the least required level but not exceeding the permissive withstand voltage level of the semiconductor devices in the inverter 4.

Fig. 5 is a block diagram showing the voltage controlling function in the inverter 4, where like components are denoted by like numerals as those shown in Fig. 1. As shown, a PWM controller 41 detects the voltage output of the inverter 4 and carries out a PWM action for maintaining the voltage output at a predetermined level.

A fuel flow controller 10 is provided having the following arrangement. Fig. 6 is a functional block diagram of a primary part of the fuel flow controller 10. A thyristor conduction angle detector 101 detects a conduction angle of the thyristors from the control signal which is transferred from the thyristor drive circuit 93 in the converter 3. The conduction angle is continuously measured at equal intervals

of time to calculate its average. The average conduction angle may preferably be a moving average of consecutive data (e.g. of ten times).

5 The average conduction angle determined by the thyristor conduction angle detector 101 is transferred to a deviation detector 102 where a deviation of the average from a target conduction angle is calculated. The deviation indicates whether or not the generator 1 is operated to produce a generous margin of the output. For the purpose, the target
10 conduction angle may be set to 80 %. The target conduction angle like a common target level has a hysteresis. The target conduction angle may be a fixed degree or may be varied depending on the temperature of the engine 2. For example, when the temperature of the engine 2 is low, the target
15 conduction angle is decreased. As its engine 2 is adjusted to a desired revolution so that the deviation detected by the deviation detector 102 is zero, the generator 1 can be operated to produce a generous margin of the output.

20 Fig. 7 illustrates a waveform of the thyristor output of the converter 3 driven with the conduction angle of 80 %. As shown, the conduction angle α is an electrical angle corresponding to a duration for conducting the thyristors and can thus be determined by a known manner.

25 A target revolution updating unit 103 includes a table of revolution adjustment for determining the adjustment of revolution in response to the deviation received as a readout

address from the deviation detector 102.

Fig. 8 illustrates the relationship between the deviation and the adjustment of revolution. The deviation is a difference between the actual conduction angle and the target conduction angle, "actual conduction angle-target conduction angle". The adjustment of revolution determined from the deviation is greater when the deviation is a positive value than that when a negative value. When the deviation is positive, that is, the angle of conduction exceeds the target conduction angle (80%), it is judged that the generator 1 is operated with a less margin. This requires the output of the generator 1 to rapidly respond to a change on the load. When the deviation is negative, the generator 1 runs with a generous margin. Accordingly, the revolution can favorably be inhibited from largely increasing or decreasing which is caused by the effect of overshoot derived from excessive response.

Returning to Fig. 6, the target revolution adjustment value is transferred from the target revolution updating unit 103 to a target revolution storage 104 where it is added with a target revolution stored so that a resultant sum is an updated target revolution. The target revolution is updated not to depart from a range between the maximum and the minimum set in a maximum/minimum revolution setting unit 105. More specifically, if the target revolution after addition with the target revolution adjustment value is out

of the range, the maximum or minimum of the range will be assigned as the adjusted target revolution. It is noted that because the thyristor conduction angle may be varied at a lower revolution by any small change in the revolution, the minimum of the range has to be specified to ensure the stability of operation with no load or less load.

The revolution of the generator 1 is measured by the revolution detector 106. From the actual revolution received from the revolution detector 106 and the target revolution received from the target revolution storage 104, a control calculator 107 calculates a control value such that the deviation of the actual revolution from the target revolution is zero, using a known manner (e.g. comparison, integration, or differentiation). A throttle controller 108 is connected to a stepping motor 7 and responsive to a resultant output of the control calculator 107 for calculating the number of pulses to drive the stepping motor 7. The stepping motor 7 is thus driven by the number of pulses to change the opening of the throttle valve 6.

In the embodiment, the average conduction angle for the thyristor bridged rectifying circuit is favorably controlled to a predetermined level (for example, 80 %) by modifying the revolution of the engine 2 to determine the output of the converter 3. This allows the generator 1 to be constantly operated to produce a generous margin of the output. More particularly, when the load is increased, the voltage output

of the converter 3 declines. In response to a signal of the declination, the conduction angle of the thyristors can be increased to offset an increase in the load. Simultaneously, as the conduction angle increases, the revolution of the engine 2 can be increased gradually but not rapidly. Because the engine is not frequently changed in the revolution, its generation of noise and consumption of fuel can successfully be reduced.

sub
A6

Also in the embodiment, the voltage output of the converter is measured at the input of the inverter. This eliminates the need of calculating an optimum revolution of the generator or engine with the use of parameters including the effective power output of the inverter, the conversion efficiency of the inverter, the power output for a revolution, and variations between the components in the generator or the effective power detector, hence facilitating the process of controlling. Moreover, the converter in the embodiment for rectifying the current output of the generator is not limited to the described thyristor bridged type but may be of any other voltage controlled type such as DC-DC voltage conversion type.

As set forth above, the feature defined in claim 1 of the present invention allows the target voltage level to be decreased when the generator runs at a lower number of revolutions, thus enabling the operation at a lower range of revolution. Also, as the target voltage level is increased

when the generator runs at a higher revolution, the operation at a higher range of revolution can be ensured without lowering the efficiency.

The feature defined in claim 2 of the present invention allows the revolution of the engine to be modified throughout its range, thus controlling the conduction to a desired rate. Moreover, the features defined in claims 3 and 4 of the present invention permit the power output to be increased or decreased at a proper speed of response corresponding to a change in the load.

1911
 1912
 1913
 1914
 1915
 1916
 1917
 1918
 1919
 1920
 1921
 1922
 1923
 1924
 1925
 1926
 1927
 1928
 1929
 1930
 1931
 1932
 1933
 1934
 1935
 1936
 1937
 1938
 1939
 1940
 1941
 1942
 1943
 1944
 1945
 1946
 1947
 1948
 1949
 1950
 1951
 1952
 1953
 1954
 1955
 1956
 1957
 1958
 1959
 1960
 1961
 1962
 1963
 1964
 1965
 1966
 1967
 1968
 1969
 1970
 1971
 1972
 1973
 1974
 1975
 1976
 1977
 1978
 1979
 1980
 1981
 1982
 1983
 1984
 1985
 1986
 1987
 1988
 1989
 1990
 1991
 1992
 1993
 1994
 1995
 1996
 1997
 1998
 1999
 2000
 2001
 2002
 2003
 2004
 2005
 2006
 2007
 2008
 2009
 2010
 2011
 2012
 2013
 2014
 2015
 2016
 2017
 2018
 2019
 2020
 2021
 2022
 2023
 2024
 2025
 2026
 2027
 2028
 2029
 2030
 2031
 2032
 2033
 2034
 2035
 2036
 2037
 2038
 2039
 2040
 2041
 2042
 2043
 2044
 2045
 2046
 2047
 2048
 2049
 2050
 2051
 2052
 2053
 2054
 2055
 2056
 2057
 2058
 2059
 2060
 2061
 2062
 2063
 2064
 2065
 2066
 2067
 2068
 2069
 2070
 2071
 2072
 2073
 2074
 2075
 2076
 2077
 2078
 2079
 2080
 2081
 2082
 2083
 2084
 2085
 2086
 2087
 2088
 2089
 2090
 2091
 2092
 2093
 2094
 2095
 2096
 2097
 2098
 2099
 2100
 2101
 2102
 2103
 2104
 2105
 2106
 2107
 2108
 2109
 2110
 2111
 2112
 2113
 2114
 2115
 2116
 2117
 2118
 2119
 2120
 2121
 2122
 2123
 2124
 2125
 2126
 2127
 2128
 2129
 2130
 2131
 2132
 2133
 2134
 2135
 2136
 2137
 2138
 2139
 2140
 2141
 2142
 2143
 2144
 2145
 2146
 2147
 2148
 2149
 2150
 2151
 2152
 2153
 2154
 2155
 2156
 2157
 2158
 2159
 2160
 2161
 2162
 2163
 2164
 2165
 2166
 2167
 2168
 2169
 2170
 2171
 2172
 2173
 2174
 2175
 2176
 2177
 2178
 2179
 2180
 2181
 2182
 2183
 2184
 2185
 2186
 2187
 2188
 2189
 2190
 2191
 2192
 2193
 2194
 2195
 2196
 2197
 2198
 2199
 2200
 2201
 2202
 2203
 2204
 2205
 2206
 2207
 2208
 2209
 2210
 2211
 2212
 2213
 2214
 2215
 2216
 2217
 2218
 2219
 2220
 2221
 2222
 2223
 2224
 2225
 2226
 2227
 2228
 2229
 2230
 2231
 2232
 2233
 2234
 2235
 2236
 2237
 2238
 2239
 2240
 2241
 2242
 2243
 2244
 2245
 2246
 2247
 2248
 2249
 2250
 2251
 2252
 2253
 2254
 2255
 2256
 2257
 2258
 2259
 2260
 2261
 2262
 2263
 2264
 2265
 2266
 2267
 2268
 2269
 2270
 2271
 2272
 2273
 2274
 2275
 2276
 2277
 2278
 2279
 2280
 2281
 2282
 2283
 2284
 2285
 2286
 2287
 2288
 2289
 2290
 2291
 2292
 2293
 2294
 2295
 2296
 2297
 2298
 2299
 2300
 2301
 2302
 2303
 2304
 2305
 2306
 2307
 2308
 2309
 2310
 2311
 2312
 2313
 2314
 2315
 2316
 2317
 2318
 2319
 2320
 2321
 2322
 2323
 2324
 2325
 2326
 2327
 2328
 2329
 2330
 2331
 2332
 2333
 2334
 2335
 2336
 2337
 2338
 2339
 2340
 2341
 2342
 2343
 2344
 2345
 2346
 2347
 2348
 2349
 2350
 2351
 2352
 2353
 2354
 2355
 2356
 2357
 2358
 2359
 2360
 2361
 2362
 2363
 2364
 2365